



HAL
open science

Automatic Approach Seeking Optimal Frequency Modulation Parameters In Chirp Inversion and Chirp Reversal Ultrasound Contrast Imaging

Amira Zaylaa, Sébastien Ménigot, Jamal Charara, Jean-Marc Girault

► **To cite this version:**

Amira Zaylaa, Sébastien Ménigot, Jamal Charara, Jean-Marc Girault. Automatic Approach Seeking Optimal Frequency Modulation Parameters In Chirp Inversion and Chirp Reversal Ultrasound Contrast Imaging. The Second Science Meeting. Doctoral School of Sciences and Technology, Lebanese University, (2012)., Jun 2012, Hadath, Lebanon. inserm-01182641

HAL Id: inserm-01182641

<https://inserm.hal.science/inserm-01182641>

Submitted on 1 Aug 2015

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

A. Zaylaa^{a,b,c}, S. Ménigot^{a,b}, J. Charara^d and J.-M. Girault^{a,b}

- a. Imaging and Brain Laboratory, Université Française Rabelais de Tours, B.P. 22, France. amira.zaylaa@etu.univ-tours.fr
- b. INSERM U930, Tours, France.
- c. P.R.A.S.E., Doctoral School of Sciences and Technology, Lebanese University, Hadath, Lebanon.
- d. Department of Physics and Electronics, Lebanese University, Hadath, Lebanon.

Imaging and Brain Laboratory

I – Introduction


State-of-the art applications involving frequency coded excitations known as chirp excitations, are cutting edge in contrast ultrasound imaging. A question may arise: How does the manufacturer select the frequency modulation parameters of chirp excitations in clinical practice? The present study aims to select, automatically, the optimal frequency modulation parameters of chirp excitations by maximizing the backscattered power using two post-processing techniques: chirp inversion and chirp reversal imaging. Why the power? As the contrast-to-tissue ratio \nearrow the power backscattered by microbubbles \nearrow

$$CTR = \frac{P_{microbubbles}}{P_{tissues}}$$

II – Materials and Methods

Simulated Microbubbles with Matlab

- \nearrow Air-filled of diameter 5 μm
- \nearrow Immersed in blood mimicking fluid
- \nearrow Motion described by Modified Plesset-Rayleigh Differential Equation




Emission/Reception

- \nearrow Transducer: Bandwidth 63%


Chirp Excitations

- \nearrow Frequency modulated \rightarrow Linear frequency modulation (FM) law
- \nearrow Initial driving pressure \rightarrow 100 kPa \rightarrow NonLinear Response
- \nearrow Envelope \rightarrow Gaussian


Transmitted Chirp ($\beta=0.03\text{MHz/s}$, $f_0=1.5\text{MHz}$)




Chirp Spectrogram




Block Diagram of Chirp Reversal and/or Chirp Inversion post-processing techniques.



Chirp Reversal



Chirp Inversion



Automatic Optimization Approach

- \nearrow Cost Function $J \rightarrow$ Resultant Backscattered Power


$$w_{k+1} = w_k + \mu_k \cdot \nabla J(w_k)$$

- \nearrow Automatic Optimization: Maximum Number of iterations $k=50$

$$\begin{pmatrix} f_{k+1} \\ \beta_{k+1} \end{pmatrix} = \begin{pmatrix} f_k \\ \beta_k \end{pmatrix} + \begin{pmatrix} \mu_{11} & \mu_{12} \\ \mu_{21} & \mu_{22} \end{pmatrix} \times \begin{pmatrix} \nabla f^P \\ \nabla \beta^P \end{pmatrix} \Rightarrow \text{Optimum}(f_o, \beta)$$

III – Simulation Results

- \nearrow Automatic versus Standard chirp reversal (currently available in literature) Gain \rightarrow 5.4 dB
- \nearrow Automatic versus Standard chirp inversion Gain \rightarrow 2.6 dB
- \nearrow Resultant backscattered power attained after 15 iterations
- \nearrow Central Transmitted frequency \nearrow 1.1 MHz
- \nearrow Frequency modulation index \nearrow 0.23 MHz/s



Processing Technique	Chirp Reversal		Chirp Inversion		
	Optimization	Modulation Law	Gain (dB)	fo (MHz)	Beta (MHz/s)
Optimization	Auto.	Stand.	Auto.	Stand.	
Modulation Law	Linear FM	Linear FM	Linear FM	Linear FM	
Gain (dB)	-24.3	-41.7	-24.5	-31.5	
fo (MHz)	2.2	3	2.2	2.75	
Beta (MHz/s)	0.23	0.2	0.23	0.1	

IV – Conclusion

- \nearrow Automatic Optimization by chirp reversal/ inversion converged to similar optimized parameters
- \nearrow Power gain by Chirp Reversal was advantageous over chirp inversion
- \nearrow Power Gain attained by automatic chirp reversal was significant compared to standard technique
- \nearrow The proposed Automatic approach may improve CTR of Ultrasound Images so we tend to validate it by experiment